



## **Transformer**

### 2240

- Double-isolated transformer
- 3.75 kVAC isolation voltage
- 30 VA ring core transformer
- Thermal overload protection
- 12 or 24 VAC secondary voltage
- Standard 11-pole relay socket



### **Advanced features**

· Two transformers may be paralleled for higher output power.

### **Application**

- Transformer for supply of components with 12 or 24 VAC supply voltage.
- Transformer for stabilized DC power supplies, e.g. type 2229.

### **Technical characteristics**

- Standard primary input voltages of 115 or 230 VAC with special primary voltages to order.
- Standard secondary voltages of 12 or 24 VAC with special secondary voltages to order.
- Ring core transformer with separate 3.75 kVAC isolation voltage between primary and secondary windings.
- · Fitted with a thermal fuse.
- The device is supplied with a retention clip for a safe attachment to the relay socket.
- Mounting for a standard 11-pole socket which can be adapted for DIN rail or plate use with PR's 7023 adaptor and 7024 mounting keying.

# Connections 115 VAC 24 VAC 230 VAC 15 VAC

### Order:

Туре	Input		Output	
2240	115 VAC	: A	Special	: 0
	230 VAC	: B	24 VAC	: 1
	Special	: X	12 VAC	: 2

### **Environmental Conditions**

Specifications range	-20°C to +60°C
Relative humidity	< 95% RH (non-cond.)
Protection degree	IP50

# **Mechanical specifications**

# Common specifications

Isolation voltage	2.75 12/40 / 250 //40
workingPELV/SELV	
Power derating EMC immunity influence	

# Input specifications

Primary voltage	207253 VAC
Primary voltage	97.75132.25 VAC
Frequency	5060 Hz

### **Output specifications**

Secondary voltage (loaded)	24 VAC / 1.25 A
Secondary voltage (unloaded)	28 VAC
Secondary voltage (loaded)	12 VAC / 2.50 A
Secondary voltage (unloaded)	14 VAC
*of span	= of the presently selected
·	range

### Observed authority requirements

EMC	 2014/30/EU

# **Approvals**

EAC......TR-CU 020/2011